arXiv:1210.5292v1 [cs.IT] 19 Oct 2012

Low-Complexity Demodulation for Interleaved OFDMA Downlink System Using Circular Convolution

Hyun-Seung Joo, Kee-Hoon Kim, Jong-Seon No[1], *Fellow, IEEE*,
and Dong-Joon Shin[2], *Senior member, IEEE*

Abstract

In this paper, a new low-complexity demodulation scheme is proposed for interleaved orthogonal frequency division multiple access (OFDMA) downlink system with N subcarriers and M users using circular convolution. In the proposed scheme, each user's signal is extracted from the received interleaved OFDMA signal of M users by using circular convolution in the time domain and then fast Fourier transformed in the reduced size N/M. It is shown that the computational complexity of the proposed scheme for the interleaved OFDMA downlink system is much less than that of the conventional one.

Index Terms

Circular convolution, low-complexity demodulation, fast Fourier transform (FFT), orthogonal frequency division multiplexing (OFDM), orthogonal frequency division multiple access (OFDMA).

I. INTRODUCTION

Orthogonal frequency division multiplexing (OFDM) can achieve high-speed data transmission in the multipath fading channel by dividing a high-rate data stream into parallel low-rate streams on orthogonal subcarriers [1], [2]. If the number of subcarriers and guard interval are large enough, channel for each subcarrier becomes approximately frequency flat and high-order modulation can be used. Due to robustness of OFDM system against the multipath fading, it

---

[1] H.-S. Joo, K.-H. Kim, and J.-S. No are with the Department of Electrical Engineering and Computer Science, INMC, Seoul National University, Seoul, 151-744, Korea (email: {joohs, kkh}@ccl.snu.ac.kr, jsno@snu.ac.kr).

[2] D.-J. Shin is with the Department of Electronic Engineering, Hanyang University, Seoul, 133-791, Korea (email: djshin@hanyang.ac.kr).

This work was supported by the Korea Science and Engineering Foundation (KOSEF) grant funded by the Korea Government (MEST) (No. 2012-0000186).

has already been adopted in various wireless communication systems such as wireless local area network (WLAN) [3], wireless metropolitan area network (WMAN) [4], and 3GPP-LTE [5].

In addition, orthogonal frequency division multiple access (OFDMA) has been adopted as one of multiple access schemes for the wireless communication networks. In OFDMA system, time or frequency resources are used to separate multiple user signals. Generally, most of users experience low battery life of mobile stations and signal processing schemes for data transmission considerably affect the power consumption. Among signal processing schemes used in mobile stations, fast Fourier transform (FFT) and inverse fast Fourier transform (IFFT) occupy a significant portion of total computational complexity [6]. Therefore, reduction of the computational complexity of FFT/IFFT in OFDMA system is highly demanded.

In OFDMA system, a portion of N subcarriers is allocated to each user but all users' data on N subcarriers are always received by each user, where N-point FFT is needed [7]. Recently, by dividing the N-point discrete Fourier transform (DFT), a low-complexity demodulation scheme is proposed for interleaved OFDMA downlink system [8]. However, this scheme can work only when the number of subcarriers allocated to each user is small. Since other users' data do not need to be exploited for each user, a method to extract the signal of each user from the received OFDMA signal is necessary for the reduced size FFT.

In this paper, a new low-complexity demodulation scheme is proposed for interleaved OFDMA downlink system with N subcarriers and M users using circular convolution. In the proposed scheme, each user's signal is extracted from the received interleaved OFDMA signal of M users by using circular convolution in the time domain and then fast Fourier transformed (FFTed) in the reduced size N/M instead of the size N. It is shown that the computational complexity of the proposed demodulation scheme is much less than that of the conventional demodulation scheme for the interleaved OFDMA downlink system.

The rest of the paper is organized as follows. In Section II, the interleaved OFDMA system is briefly introduced. In Section III, user signal extraction matrices are proposed for the interleaved OFDMA downlink system. In Section IV, a new low-complexity demodulation scheme for the interleaved OFDMA downlink system using circular convolution is proposed. The computational complexity of the proposed demodulation scheme is analyzed in Section V. Finally, conclusion is given in Section VI.



Fig. 1. An interleaved OFDMA of four users with $N = 16$ in the frequency domain.

II. INTERLEAVED OFDMA SYSTEM

In OFDMA downlink system, a data bit stream is mapped into an input symbol vector $\mathbf{X} = [X_0\ X_1\ \cdots\ X_{N-1}]^T$ modulated by PSK or QAM, where N is the number of subcarriers and $(\cdot)^T$ denotes the transpose of a vector. Note that a high-rate data stream of M users is split into N low-rate data streams, which are loaded on the N subcarriers. By IFFTing the input symbol vector $\mathbf{X}$, i.e., $\mathbf{x} = \mathrm{IFFT}(\mathbf{X})$, an OFDMA signal is obtained as

$$x_n = \frac{1}{\sqrt{N}} \sum_{k=0}^{N-1} X_k e^{j\frac{2\pi kn}{N}}, \quad 0 \le n \le N-1 \tag{1}$$

where $j = \sqrt{-1}$ and $\mathbf{x} = [x_0\ x_1\ \cdots\ x_{N-1}]^T$ is the OFDMA signal vector. Each OFDMA signal of M users is transmitted over an independent multipath fading channel.

Since the interleaved OFDMA downlink system is considered in this paper, we assume that the N subcarriers are partitioned into M disjoint interleaved subcarrier groups for M users by taking every Mth subcarrier. Then, an input symbol vector $\mathbf{X}$ is partitioned into M disjoint user symbol vectors $\mathbf{X}_m$ according to these subcarrier groups as

$$\mathbf{X} = \sum_{m=1}^{M} \mathbf{X}_m \tag{2}$$

where $\mathbf{X}_m = [X_{m,0}\ X_{m,1}\ \cdots\ X_{m,N-1}]^T$, $1 \leq m \leq M$, is given as

$$X_{m,k} = \begin{cases} X_k, & \text{if } k = m-1 \bmod M \\ 0, & \text{otherwise.} \end{cases} \tag{3}$$

Clearly, each subcarrier is allocated to only one user and all subcarriers in the mth subcarrier group is assigned to the mth user. Thus, for each user, the number of assigned subcarriers is N/M. Fig. 1 shows an interleaved OFDMA of four users in frequency domain.

Suppose that the received signal vector at the receiver of the mth user is $\mathbf{r} = [r_0\ r_1\ \cdots\ r_{N-1}]^T$ in time domain. Then, the received symbol vector $\mathbf{R} = [R_0\ R_1\ \cdots\ R_{N-1}]^T$ is obtained by N-point FFT of $\mathbf{r}$. Finally, the mth user can obtain the received user symbol vector $\mathbf{R}_m = [R_{m,0}\ R_{m,1}\ \cdots\ R_{m,N-1}]^T$, $1 \leq m \leq M$, from the received symbol vector $\mathbf{R}$ to extract its own data. Fig. 2 shows a block diagram of the conventional OFDMA downlink system.

III. USER SIGNAL EXTRACTION MATRIX FOR INTERLEAVED OFDMA SIGNALS

In this section, a new approach to extract the mth user signal from the interleaved OFDMA downlink signal is proposed.

A. *Derivation of User Signal Extraction Matrix*

Let $\mathbf{x}_m = [x_{m,0}\ x_{m,1}\ \cdots\ x_{m,N-1}]^T$, $1 \leq m \leq M$, denote the mth user signal vector which is an IFFT output of the mth user symbol vector $\mathbf{X}_m$ as $\mathbf{x}_m = \mathrm{IFFT}(\mathbf{X}_m)$. By using the linear property of IFFT, the OFDMA signal vector $\mathbf{x}$ can be written as

$$\mathbf{x} = \sum_{m=1}^{M} \mathbf{x}_m. \tag{4}$$

Now, we derive the user signal extraction matrix to extract $\mathbf{x}_m$ from $\mathbf{x}$ as follows. First, let $\mathbf{P}_m = [P_{m,0}\ P_{m,1} \cdots P_{m,N-1}]^T$ be the mth user signal extraction vector, where $P_{m,k} \in \{0, 1\}$, $1 \leq m \leq M$ and $0 \leq k \leq N-1$. If the subcarrier k is allocated to the mth user, $P_{m,k} = 1$ and otherwise $P_{m,k} = 0$. Then, the mth user symbol vector $\mathbf{X}_m$ can be expressed as

$$\begin{aligned} \mathbf{X}_m &= [P_{m,0}X_0\ P_{m,1}X_1\ \cdots\ P_{m,N-1}X_{N-1}]^T \\ &= \mathbf{M}_m \mathbf{X} \end{aligned} \tag{5}$$



(a)

(b)

Fig. 2. A block diagram of the conventional OFDMA downlink system: (a) Transmitter of the base station and (b) receiver of the mobile station for the mth user.

where

$$\mathbf{M}_m = \begin{bmatrix} P_{m,0} & 0 & \cdots & 0 \\ 0 & P_{m,1} & \ddots & \vdots \\ \vdots & \ddots & \ddots & 0 \\ 0 & \cdots & 0 & P_{m,N-1} \end{bmatrix} \tag{6}$$

is an $N \times N$ diagonal matrix corresponding to the mth user signal extraction vector $\mathbf{P}_m$. Then, the mth user signal vector $\mathbf{x}_m$ can be rewritten as

$$\mathbf{x}_m = \mathrm{IFFT}(\mathbf{X}_m) = \mathbf{Q}\mathbf{M}_m\mathbf{X} \tag{7}$$

where

$$\mathbf{Q} = \frac{1}{\sqrt{N}} \begin{bmatrix} 1 & 1 & 1 & \cdots & 1 \\ 1 & W_N^{-1} & W_N^{-2} & \cdots & W_N^{-(N-1)} \\ 1 & W_N^{-2\cdot 1} & W_N^{-2\cdot 2} & \cdots & W_N^{-2(N-1)} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ 1 & W_N^{-(N-1)\cdot 1} & W_N^{-(N-1)\cdot 2} & \cdots & W_N^{-(N-1)\cdot(N-1)} \end{bmatrix} \tag{8}$$

is the IFFT matrix with $W_N = e^{-j\frac{2\pi}{N}}$. Since $\mathbf{x} = \mathrm{IFFT}(\mathbf{X}) = \mathbf{Q}\mathbf{X}$, the input symbol vector is expressed as

$$\mathbf{X} = \mathbf{Q}^{-1}\mathbf{x} \tag{9}$$

where $\mathbf{Q}^{-1}$ denotes the FFT matrix. From (7) and (9), the mth user signal vector $\mathbf{x}_m$ can be obtained as

$$\mathbf{x}_m = \mathbf{Q}\mathbf{M}_m\mathbf{Q}^{-1}\mathbf{x}. \tag{10}$$

Therefore, the following mth user signal extraction matrix $\mathbf{T}_m$ can be used to directly extract $\mathbf{x}_m$ from $\mathbf{x}$:

$$\mathbf{T}_m = \mathbf{Q}\mathbf{M}_m\mathbf{Q}^{-1}. \tag{11}$$

By using the convolution property of IFFT, the user signal extraction matrix $\mathbf{T}_m$ can be expressed by using the user signal extraction vector $\mathbf{P}_m$ [9]. From (10), it is easy to see that the mth user signal vector $\mathbf{x}_m$ can be generated by a circular convolution of the OFDMA signal vector $\mathbf{x}$ and the IFFTed user signal extraction vector of $\mathbf{P}_m$ as

$$\mathbf{x}_m = \mathrm{IFFT}(\mathbf{P}_m) \otimes_N \mathbf{x} \tag{12}$$

where $\otimes_N$ denotes the N-point circular convolution. Let $\mathbf{t}_m = [t_{m,0}\ t_{m,1}\ \cdots\ t_{m,N-1}]^T = \mathrm{IFFT}(\mathbf{P}_m)$, that is,

$$t_{m,n} = \frac{1}{\sqrt{N}}\sum_{k=0}^{N-1} P_{m,k}e^{j\frac{2\pi kn}{N}}. \tag{13}$$

Then, the mth user signal vector $\mathbf{x}_m$ can be rewritten as

$$\mathbf{x}_m = \mathbf{t}_m \otimes_N \mathbf{x} \tag{14}$$

and thus

$$x_{m,n} = \sum_{v=0}^{N-1} t_{m,v}x_{n-v} \tag{15}$$

where the subscript $n-v$ is computed by modulo N.

From (11) and (12), it is easy to see that $\mathbf{T}_m$ is a circulant matrix and $\mathbf{t}_m$ is the first column vector of $\mathbf{T}_m$. Then, the mth user signal extraction matrix $\mathbf{T}_m$ can be rewritten as

$$\mathbf{T}_m = [\mathbf{t}_m^{<0>}\ \mathbf{t}_m^{<1>}\ \mathbf{t}_m^{<2>}\ \cdots\ \mathbf{t}_m^{<N-1>}] \tag{16}$$

where $\mathbf{t}_m^{<\tau>}$ is a circularly down-shifted version of the column vector $\mathbf{t}_m$ by τ. From (16), if the user signal extraction vector $\mathbf{P}_m$ is given, the column vector $\mathbf{t}_m$ and the corresponding user signal extraction matrix $\mathbf{T}_m$ can be determined.

B. User Signal Extraction Matrices for Interleaved OFDMA Downlink System

For OFDMA system, there are several schemes to multiplex $\mathbf{x}_m$ into $\mathbf{x}$, that is, adjacent, interleaved, and random subcarrier allocation schemes [10]. However, adjacent and random subcarrier allocation schemes are not efficiently implemented by using $\mathbf{T}_m$ derived in Subsection III.A because most of the elements in $\mathbf{t}_m$ are nonzero. Therefore, the computational complexity of the circular convolution between $\mathbf{t}_m$ and $\mathbf{x}$ may be larger than that of IFFT. On the other hand, the interleaved subcarrier allocation scheme is suitable for the implementation using $\mathbf{T}_m$ because there are a few nonzero elements in $\mathbf{t}_m$.

The element of the mth user signal extraction vector $\mathbf{P}_m$ for the interleaved OFDMA system is given as

$$P_{m,k} = \begin{cases} 1, & k = Mi + m - 1 \\ 0, & \text{otherwise} \end{cases} \tag{17}$$

where $0 \le i \le N/M - 1$ and $1 \le m \le M$. From (17), the elements of $\mathbf{t}_m$ for the interleaved OFDMA system are derived as

$$\begin{aligned} t_{m,n} &= \frac{1}{\sqrt{N}} \sum_{k=0}^{N-1} P_{m,k} e^{j\frac{2\pi kn}{N}} \\ &= \frac{1}{\sqrt{N}} \sum_{i=0}^{N/M-1} e^{j\frac{2\pi(Mi+m-1)n}{N}} \\ &= \frac{1}{\sqrt{N}} e^{j\frac{2\pi(m-1)n}{N}} \sum_{i=0}^{N/M-1} \left(e^{j\frac{2\pi nM}{N}} \right)^i \\ &= \begin{cases} \frac{\sqrt{N}}{M} e^{j\frac{2\pi(m-1)}{M}l}, & n = \frac{N}{M}l \\ 0, & \text{otherwise} \end{cases} \end{aligned} \tag{18}$$

where $0 \le l \le M-1$ and $0 \le n \le N-1$. All the elements in $\mathbf{t}_m$ for the interleaved subcarrier allocation scheme are zero except for M nonzero elements at $n = \frac{N}{M}l$, which take the values from $\{\frac{\sqrt{N}}{M} e^{j\frac{2\pi}{M}\cdot 0}, \frac{\sqrt{N}}{M} e^{j\frac{2\pi}{M}\cdot 1}, \cdots, \frac{\sqrt{N}}{M} e^{j\frac{2\pi}{M}\cdot(M-1)}\}$. Thus, the column vector $\mathbf{t}_m$ is expressed as

$$\begin{aligned} \mathbf{t}_m = \frac{\sqrt{N}}{M} \Bigg[& \underbrace{1\ 0 \cdots 0}_{\frac{N}{M}}\ \underbrace{e^{j\frac{2\pi(m-1)}{M}}\ 0 \cdots 0}_{\frac{N}{M}}\ \underbrace{e^{j\frac{2\pi(m-1)}{M}2}\ 0 \cdots 0}_{\frac{N}{M}} \\ & \cdots\ \underbrace{e^{j\frac{2\pi(m-1)}{M}(M-2)}\ 0 \cdots 0}_{\frac{N}{M}}\ \underbrace{e^{j\frac{2\pi(m-1)}{M}(M-1)}\ 0 \cdots 0}_{\frac{N}{M}} \Bigg]^T . \end{aligned} \tag{19}$$

For example, if $M = 2$,

$$\mathbf{t}_1 = \frac{\sqrt{N}}{2}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{2}}\ \underbrace{1\ 0\cdots 0}_{\frac{N}{2}}\right]^T$$

$$\mathbf{t}_2 = \frac{\sqrt{N}}{2}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{2}}\ \underbrace{-1\ 0\cdots 0}_{\frac{N}{2}}\right]^T \tag{20}$$

and if $M = 4$,

$$\mathbf{t}_1 = \frac{\sqrt{N}}{4}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\right]^T$$

$$\mathbf{t}_2 = \frac{\sqrt{N}}{4}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{j\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-j\ 0\cdots 0}_{\frac{N}{4}}\right]^T$$

$$\mathbf{t}_3 = \frac{\sqrt{N}}{4}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-1\ 0\cdots 0}_{\frac{N}{4}}\right]^T$$

$$\mathbf{t}_4 = \frac{\sqrt{N}}{4}\left[\underbrace{1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-j\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{-1\ 0\cdots 0}_{\frac{N}{4}}\ \underbrace{j\ 0\cdots 0}_{\frac{N}{4}}\right]^T. \tag{21}$$

For $M = 2$ or 4, to generate the mth user signal vector $\mathbf{x}_m$, $(M-1)N$ complex additions for the circular convolution of $\mathbf{t}_m$ and $\mathbf{x}$ are only required because the multiplication by $\{\pm 1, \pm j\}$ can be ignored. However, for $M > 4$, $(M-1)N$ complex additions and $(M-4)N$ complex multiplications are required for the circular convolution of $\mathbf{x}$ and $\mathbf{t}_m$ if the complex multiplications by $e^{j\frac{2\pi(m-1)}{M}l} \in \{\pm 1, \pm j\}$, $0 \le l \le M-1$, are ignored.

IV. LOW-COMPLEXITY DEMODULATION FOR INTERLEAVED OFDMA DOWNLINK SYSTEM

In this section, an algorithm to reduce the computational complexity of FFT for the demodulation of each user's signal in the interleaved OFDMA downlink system is proposed.

A. Subvector Rotation Expression of the mth User Signal Vector

Since $\mathbf{t}_m$ has only M nonzero elements, from (15) and (18), the nth element of the mth user signal vector $\mathbf{x}_m$ is expressed as

$$x_{m,n} = \sum_{v=0}^{N-1} t_{m,v} x_{n-v} = \frac{\sqrt{N}}{M} \sum_{l=0}^{M-1} e^{j\frac{2\pi(m-1)}{M}l} x_{n-\frac{N}{M}l} \tag{22}$$

where the subscript of $x_{n-\frac{N}{M}l}$ is computed by modulo N. By using the property of circular convolution, (22) can be written as

$$x_{m,n+\frac{N}{M}s} = \frac{\sqrt{N}}{M} \sum_{l=0}^{M-1} e^{j\frac{2\pi(m-1)}{M}l} x_{n+\frac{N}{M}s-\frac{N}{M}l} = e^{j\frac{2\pi(m-1)}{M}s} x_{m,n} \tag{23}$$

where $0 \le s \le M-1$. Let $\mathbf{x}_m = \left[{\mathbf{x}_m^0}^T \; {\mathbf{x}_m^1}^T \; \cdots \; {\mathbf{x}_m^{M-1}}^T \right]^T$, where $\mathbf{x}_m^s = [x_{m,\frac{N}{M}s} \; x_{m,\frac{N}{M}s+1} \cdots x_{m,\frac{N}{M}(s+1)-1}]^T$ is the sth subvector of the mth user signal vector. From (23), $\mathbf{x}_m$ can be expressed as

$$\mathbf{x}_m = \left[{\mathbf{x}_m^0}^T \; e^{j\frac{2\pi(m-1)}{M}} {\mathbf{x}_m^0}^T \; \cdots \; e^{j\frac{2\pi(m-1)}{M}(M-1)} {\mathbf{x}_m^0}^T \right]^T \tag{24}$$

where $\mathbf{x}_m^s = e^{j\frac{2\pi(m-1)}{M}s}\mathbf{x}_m^0$, $1 \le s \le M-1$ and $1 \le m \le M$. Note that (24) implies that the first N/M elements in each user signal vector can be used to generate the other $(M-1)N/M$ elements only through the phase rotation by $\frac{2\pi(m-1)}{M}s$, $1 \le s \le M-1$. As a result, the circular convolution for the first subvector of the mth user signal vector is only required because the remaining subvectors can be obtained directly from the phase rotation of the first subvector. Therefore, $x_{m,n}$ in (22) needs to be computed only for $0 \le n \le N/M-1$.

B. Low-Complexity Demodulation Scheme

In an interleaved OFDMA downlink system, each user receives the OFDMA signal conveying all M users' data. In general, the mth user symbol vector $\mathbf{X}_m$ is recovered by performing N-point FFT to the received OFDMA signal vector $\mathbf{r}$ in the conventional OFDMA system. However, in the proposed low-complexity demodulation scheme for the interleaved OFDMA downlink system, the received mth user signal vector $\mathbf{r}_m$ is extracted from the received OFDMA signal vector $\mathbf{r}$, and then N/M-point FFT is performed to $\mathbf{r}_m$ to obtain the mth user symbol vector $\mathbf{X}_m$ as will be explained below. Thus, each user does not need to do N-point FFT generating unnecessary other users' data.

Similar to $\mathbf{x}_m$ in (14), the received mth user signal vector $\mathbf{r}_m$ can be extracted as

$$\mathbf{r}_m = \mathbf{t}_m \otimes_N \mathbf{r} \tag{25}$$

where $\mathbf{r}_m = [r_{m,0}\ r_{m,1}\ \cdots\ r_{m,N-1}]^T$. As described in Subsection IV-A, the first received subvector $\mathbf{r}_m^0$ of length N/M in the received mth user signal vector $\mathbf{r}_m = [\mathbf{r}_m^{0\ T}\ \mathbf{r}_m^{1\ T}\ \cdots\ \mathbf{r}_m^{M-1T}]^T$ is computed and the remaining received subvectors $\mathbf{r}_m^s$, $1 \leq s \leq M-1$, are obtained through the phase rotation of $\mathbf{r}_m^0$ by $\frac{2\pi(m-1)}{M}s$. It is clear that the BER performance of the interleaved OFDMA downlink system is not degraded by the proposed demodulation scheme.

The kth symbol $R_{m,k}$ after performing N-point FFT of $\mathbf{r}_m$ at the receiver of the mth user is expressed as

$$R_{m,k} = \frac{1}{\sqrt{N}} \sum_{n=0}^{N-1} r_{m,n} e^{-j\frac{2\pi kn}{N}}, \quad 0 \leq k \leq N-1. \tag{26}$$

To demodulate the mth user signal, we are only interested in the mth subcarrier group. Therefore, we will only consider the symbols $R_{m,Mi+m-1}$, $0 \leq i \leq N/M-1$, given as

$$R_{m,Mi+m-1} = \frac{1}{\sqrt{N}} \sum_{n=0}^{N-1} r_{m,n} e^{-j\frac{2\pi(Mi+m-1)n}{N}}. \tag{27}$$

Similar to (22), the received mth user symbol $R_{m,Mi+m-1}$ in (27) can be expressed as

$$\begin{aligned} R_{m,Mi+m-1} &= \frac{1}{\sqrt{N}} \sum_{s=0}^{M-1} \sum_{n=0}^{\frac{N}{M}-1} e^{j\frac{2\pi(m-1)s}{M}} r_{m,n} e^{-j\frac{2\pi(Mi+m-1)\left(\frac{N}{M}s+n\right)}{N}} \\ &= \frac{1}{\sqrt{N}} \sum_{s=0}^{M-1} \sum_{n=0}^{\frac{N}{M}-1} r_{m,n} e^{-j2\pi is} e^{-j\frac{2\pi(Mi+m-1)n}{N}} \\ &= \frac{M}{\sqrt{N}} \sum_{n=0}^{\frac{N}{M}-1} \left(r_{m,n} e^{-j\frac{2\pi(m-1)n}{N}} \right) e^{-j\frac{2\pi in}{N/M}}. \end{aligned} \tag{28}$$

From (28), it is easy to see that N/M data symbols $R_{m,Mi+m-1}$, $0 \leq i \leq N/M-1$, of the mth user can be obtained by applying N/M-point FFT. In order to directly perform the N/M-point FFT, the modified mth user signal is defined as

$$\bar{r}_{m,n} = \sqrt{M} e^{-j\frac{2\pi(m-1)n}{N}} r_{m,n}, \quad 0 \leq n \leq \frac{N}{M}-1 \tag{29}$$

where $\bar{\mathbf{r}}_m = [\bar{r}_{m,0}\ \bar{r}_{m,1}\ \cdots\ \bar{r}_{m,\frac{N}{M}-1}]^T$. Let $\bar{\mathbf{R}}_m = [\bar{R}_{m,0}\ \bar{R}_{m,1}\ \cdots\ \bar{R}_{m,\frac{N}{M}-1}]^T$ be the demodulated mth user symbol vector consisting of N/M data symbols of the mth user as $\bar{R}_{m,i} = R_{m,Mi+m-1}$, $0 \leq i \leq N/M-1$. Then, $\bar{\mathbf{R}}_m$ can be obtained by performing N/M-point FFT to $\bar{\mathbf{r}}_m$ as

$$\bar{\mathbf{R}}_m = \mathrm{FFT}(\bar{\mathbf{r}}_m). \tag{30}$$



Fig. 3. A block diagram of the proposed demodulation scheme for the mth user.

Fig. 3 shows the structure of the proposed demodulation scheme at the receiver of the mth user. The proposed demodulation scheme requires the computational complexity to obtain $\bar{\mathbf{r}}_m$ from $\mathbf{r}$ using user signal extraction matrix and the computational complexity of N/M-point FFT. For $M = 2$ or 4, the computational complexity of circular convolution to obtain $\bar{\mathbf{r}}_m$ is given as $(M-1)N/M$ complex additions because only the first N/M elements of $\mathbf{r}$ needs to be calculated, where the complex multiplication by $\{\pm 1, \pm j\}$ is ignored. When $M > 4$, $(M-1)N/M$ complex additions and $(M-4)N/M$ complex multiplications are required for the proposed demodulation scheme, where the complex multiplication is ignored if $e^{j\frac{2\pi(m-1)}{M}s} \in \{\pm 1, \pm j\}$, $0 \le s \le M-1$. It is clear that the computational complexity of the proposed demodulation scheme is much smaller than that of the conventional N-point FFT, which will be analyzed in the next section.

V. COMPUTATIONAL COMPLEXITY ANALYSIS

In this section, the computational complexity of the proposed demodulation scheme is analyzed. In order to recover the user symbol vector in the interleaved OFDMA downlink system, one N-point FFT at each receiver is generally required, where the number of complex multiplications and additions for the N-point FFT are $(N/2)\log_2 N$ and $N \log_2 N$, respectively. In the proposed demodulation scheme, the computation to obtain $\bar{\mathbf{r}}_m$ from $\mathbf{r}$ and one N/M-point FFT operation for each user are needed. Table I compares the computational complexity of the conventional N-point FFT scheme and the proposed demodulation scheme for the interleaved OFDMA downlink system, where the multiplication by an element in $\{\pm 1, \pm j\}$ is ignored.

In order to obtain the received mth user signal vector $\mathbf{r}_m$ by the proposed user signal extraction scheme, circular convolution to calculate the first N/M elements of $\mathbf{t}_m \otimes_N \mathbf{r}$ is required and for $M = 2$ and 4, additional $N/2$ and $3N/4$ complex additions are required, respectively. When $M > 4$, the total number of complex additions to calculate $\mathbf{t}_m \otimes_N \mathbf{r}$ is still $(M-1)N/M$, and

TABLE I

COMPUTATIONAL COMPLEXITY OF THE CONVENTIONAL AND PROPOSED DEMODULATION SCHEMES FOR THE INTERLEAVED OFDMA DOWNLINK SYSTEM WITH N SUBCARRIERS AND M USERS

	Total number of complex multiplications	Total number of complex additions
Conventional N-point FFT scheme	$\frac{N}{2}\log_2 N$	$N\log_2 N$
Proposed scheme ($M = 2, 4$)	$\frac{N}{2M}\log_2\frac{N}{M} + \frac{N}{M}$	$\frac{N}{M}\log_2\frac{N}{M} + \frac{(M-1)N}{M}$
Proposed scheme ($M > 4$)	$\frac{N}{2M}\log_2\frac{N}{M} + \frac{(M-3)N}{M}$	$\frac{N}{M}\log_2\frac{N}{M} + \frac{(M-1)N}{M}$

$(M-4)N/M$ complex multiplications are needed if the complex multiplication by $e^{j\frac{2\pi(m-1)}{M}s} \in \{\pm 1, \pm j\}$, $0 \le s \le M-1$, is ignored. To convert $\mathbf{r}_m$ to $\bar{\mathbf{r}}_m$, N/M complex multiplications are required. Finally, $(N/2M)\log_2(N/M)$ complex multiplications and $(N/M)\log_2(N/M)$ complex additions are required for N/M-point FFT computation of $\bar{\mathbf{r}}_m$. Fig. 4 compares the computational complexity of the conventional N-point FFT scheme and the proposed demodulation scheme for $N = 1024$. Fig. 4 shows that the number of complex multiplications and complex additions required for the proposed demodulation scheme is much less than that of the conventional N-point FFT scheme.

To more practically compare the proposed demodulation scheme with the conventional N-point FFT scheme, the total number of flops are counted. It is known that one complex multiplication and one complex addition involve 6 flops and 2 flops, respectively [11]. Fig. 5 compares the total number of flops for N-point FFT and the proposed demodulation scheme for $N = 1024$. From Fig. 5, it is shown that the computational complexity to generate the mth user symbol vector is considerably reduced by using the proposed demodulation scheme.

The computational complexity reduction ratio (CCRR) [12] of the proposed demodulation scheme over the conventional N-point FFT scheme is defined as

$$\mathrm{CCRR} = \left(1 - \frac{\text{Complexity of the proposed scheme}}{\text{Complexity of } N\text{–point FFT}}\right) \times 100\ (\%). \tag{31}$$

The CCRR of the proposed demodulation scheme over N-point FFT for various N is given in Table II, which clearly shows that the proposed demodulation scheme is computationally much

TABLE II

CCRR OF THE PROPOSED DEMODULATION SCHEME OVER N-POINT FFT FOR $N = 512$, 1024, AND 2048

N	512				1024				2048			
M	4	8	16	32	4	8	16	32	4	8	16	32
Complex multiplications	75	77.8	78.5	78.5	75	78.8	80	80.3	75	79.5	81.3	81.8
Complex additions	72.2	81.9	86.1	87.8	72.5	82.5	86.9	88.8	72.7	83	87.5	89.5
Flops	73.9	79.4	81.5	82.2	74	80.3	82.8	83.7	74.1	80.9	83.75	84.9

more efficient than the conventional one. In Table II, it is shown that the proposed demodulation scheme can reduce the computational complexity by about 80 % compared to N-point FFT. Also, while the demodulation scheme dividing DFT in [8] is useful for small N/M, the computational complexity of the proposed demodulation scheme is always much lower than that of N-point FFT regardless of the value of N/M.

VI. CONCLUSION

In this paper, we proposed a new low-complexity demodulation scheme for the interleaved OFDMA downlink system using the user signal extraction matrix. It is shown that the column vector of user signal extraction matrix for the interleaved subcarrier group consists of $N - M$ zero elements and M nonzero elements. Using circular convolution of the received OFDMA signal vector and the column vector of user signal extraction matrix in the time domain, the received mth user signal vector can be extracted from the received OFDMA signal containing M users' data and the N/M-point FFT is applied to the modified mth user signal. Since the computational complexity of the proposed demodulation scheme is much lower than that of the N-point FFT without BER degradation, it can be a good candidate demodulation scheme for the interleaved OFDMA downlink system.

REFERENCES

[1] R. van Nee and R. Prasad, *OFDM for Wireless Multimedia Communications*. Boston, MA: Arthech House, 2000.

[2] J. Tellado, *Multicarrier Modulation with Low PAR: Applications to DSL and Wireless*. Boston, MA: Kluwer Academic Publisher, 2000.

[3] IEEE, "Wireless LAN medium access control (MAC) and physical layer (PHY) specifications amendment 5: Enhancements for higher throughput," IEEE Std 802.11n, Oct. 2009.

[4] IEEE, “IEEE standard for local and metropolitan area networks part 16: Air interface for fixed broadband wireless access systems,” IEEE Std 802.16e-2005, 2005.

[5] “Evolved universal terrestrial radio access (EUTRA): Physical channels and modulation,” 3GPP TS 36.201 v8.6.0, Mar. 2009.

[6] Y. Chen, J. Zhang, and A. D. S. Jayalath, “Estimation and compensation of clipping noise in OFDMA systems,” *IEEE Trans. Wireless Commun.*, vol. 9, no. 2, pp. 523–527, Feb. 2010.

[7] S.-H. Wang, J.-C. Sie, C.-P. Li, and Y.-F. Chen, “A low-complexity PAPR reduction scheme for OFDMA uplink systems,” *IEEE Trans. Wireless Commun.*, vol. 10, no. 4, pp. 1242–1251, Apr. 2011.

[8] C.-H. Liu, “A low complexity receiver for OFDMA systems at downlink,”, in *Proc. GLOBECOM*, Taiwan, Nov.-Dec. 2009.

[9] A. V. Oppenheim and R. W. Schafer, *Discrete-Time Signal Processing*. 3rd ed., Boston, MA: Prentice Hall, 2009.

[10] D. Kivanc, G. Li, and H. Liu, “Computationally efficient bandwidth allocation and power control for OFDMA,” *IEEE Trans. Wireless Commun.*, vol. 2, no. 6, pp. 1150–1158, Nov. 2003.

[11] Z. Shen, R. Chen, J. G. Andrews, R. W. Heath, and B. L. Evans, “Low complexity user selection algorithms for multiuser MIMO systems with block diagonalization,” *IEEE Trans. Signal Process.*, vol. 54, no. 9, pp. 3658–3663, Sep. 2006.

[12] D.-W. Lim, C.-W. Lim, J.-S. No, and H. Chung, “A new PTS OFDM scheme with low complexity for PAPR reduction,” *IEEE Trans. Broadcast.*, vol. 52, no. 1, pp. 77–82, Mar. 2006.



(a)

(b)

Fig. 4. Comparison of the computational complexity of the conventional N-point FFT scheme and the proposed demodulation scheme for $N = 1024$ with $M = 4, 8, 16,$ and 32: (a) The number of complex multiplications and (b) the number of complex additions.



Fig. 5. Comparison of the number of flops in the conventional N-point FFT scheme and the proposed demodulation scheme for $N = 1024$ with $M = 4, 8, 16,$ and 32.